

GAS


CONTINUOUS POWER

POWER
A Guangdong Power Company

© Guangdong 2025. The information contained in this brochure is for guidance only and does not form part of any contract. The accuracy cannot be guaranteed as Honny have an ongoing process of development and reserve the right to change the specification of their products without notice.

Gas Generator Set

Model: G600NG



SERVICE		COP	COP
POWER	kVA	609,2	750,5
POWER	kW	609,2	6004
RATED SPEED	r.p.m.	1.500	
MAIN VOLTAGE	V	400/230 V	
AVAILABLE VOLTAGES	V	200/115 · 230 V (t)	
RATED AT POWER FACTOR	Cos Phi	1	0,8



INDUSTRIAL RANGE

Guangdong Power Company with quality certification ISO 9001
 Guangdong gensets are compliant with EC mark which includes the following directives:

- 2006/42/CE Machinery safety.
- 2014/30/UE Electromagnetic compatibility.
- 2014/35/UE electrical equipment designed for use within certain voltage limits
- 2000/14/EC Sound Power level. Noise emissions outdoor equipment. (amended by 2005/88/EC)
- EN 12100, EN 13857, EN 60204

Ambient conditions of reference according to ISO 8528-1:2018 normative: 1000 mbar, 25°C, 30% relative humidity.

Prime Power (PRP):
 According to ISO 8528-1:2018, Prime power is the maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load when operated for an unlimited number of hours per year under the agreed operating conditions with the maintenance intervals and procedures being carried out as prescribed by the manufacturer. The permissible average power output (Ppp) over 24 h of operation shall not exceed 70 % of the PRP.

Continuous Power (COP): According to Standard ISO 8528-1:2018, this is the maximum power available for continuous loads for unlimited running hours a year between the maintenance times recommended by the manufacturer under the environmental conditions established by the same.



OPEN SKID



OPEN SKID



WATER-COOLED



THREE PHASE



50 HZ



NATURAL GAS

Gas Generator Set

Model: G600NG



Engine Specifications | 1.500 r.p.m.

Rated Engine Output (COP)	kW	630
Manufacturer	Guangdong Power	
Model	G600NG	
Engine Type	4-stroke Otto Cycle	
Injection Type	Carburization	
Aspiration Type	Turbocharged	
Number of cylinders and arrangement	12-V	
Bore and Stroke	mm	152 x 165
Displacement	L	35,9
Cooling System	Water + Antifreeze	
Lube Oil Specifications	SAE 40	
Compression Ratio	11,6	

Fuel Consumption 100% COP	kW	1568
Fuel Consumption 80 % COP	kW	1286
Fuel Consumption 75 % COP	kW	1206,06
Fuel Consumption 50 % COP	kW	865,64
Fuel Consumption 25 % COP	kW	508,42
Lube oil consumption with full load	g/kWh	0,35
Total oil capacity	L	174
Heat dissipated by coolant	kW	546
Governor	Type	Electrical
Air Filter	Type	Semi-humid

- 
- Natural Gas engine
 - 4-stroke cycle
 - Water-cooled
 - Radiator with pusher fan
 - HTW sender
 - LOP sender
 - Electronic governor
 - Hot parts protection
 - Moving parts protection



Generator Specifications | STAMFORD

Manufacturer	STAMFORD	
Model	HCI634H	
Poles	No.	4
Connection type (standard)	Star-series	
Mounting type	S-00 18"	
Insulation	Class	H class

Enclosure (according IEC-34-5)	IP23
Exciter system	Self-excited, brushless
Voltage regulator	A.V.R. (Electronic)
Bracket type	Double drive-shaft
Coupling system	Elastic Coupling
Coating type	Standard (Vacuum impregnation)


- 
- Self-excited and self-regulated
 - 4 poles
 - IP23 protection
 - H class insulation
 - Double drive-shaft

Gas Generator Set

Model: G600NG

WEIGHT AND DIMENSIONS

Standard Version		
Length (L)	mm	Ask
Height (H)	mm	Ask
Width (W)	mm	Ask
Weight with liquids in radiator and sump		Ask
Autonomy	Hours	Ask



APPLICATION DATA

EXHAUST SYSTEM

Maximum exhaust temperature	°C	370
Exhaust Gas Flow	kg/s	0,92
Maximum allowed back pressure	mm H2o	450

STARTING SYSTEM

Auxiliary Voltage	Vdc	12
-------------------	-----	----

NECESSARY AMOUNT OF AIR

Cooling Air Flow	m³/s	12,25
Alternator fan air flow	m³/s	1,614

FUEL SYSTEM

Fuel Oil Specifications	Natural Gas
Composition *	95% Methane
Fuel supply pressure	mbar 50 - 240



Gas ramp


- Manual shut-off valve
- Gas filter
- Double solenoid valve
- High pressure regulator
- Primary pressure regulator
- Low pressure switch
- High pressure switch
- Valve (tightness) testing system
- Inlet pressure manometer
- Outlet pressure manometer
- Special Start/Stop sequence

Gas Generator Set

Model: G600NG

WEIGHT AND DIMENSIONS

Standard Version		
Length (L)	mm	12.192
Height (H)	mm	2.896
Width (W)	mm	2.438
Maximum shipping volume	m ³	86,08
Weight with liquids in radiator and sump	Kg	Ask
Autonomy	Hours	Ask



APPLICATION DATA

EXHAUST SYSTEM

Maximum exhaust temperature	°C	370
Exhaust Gas Flow	kg/s	0,92
Maximum allowed back pressure	mm H2o	450

STARTING SYSTEM

Auxiliary Voltage	Vdc	12
-------------------	-----	----

NECESSARY AMOUNT OF AIR

Cooling Air Flow	m ³ /s	12,25
Alternator fan air flow	m ³ /s	1,614

FUEL SYSTEM

Fuel Oil Specifications	Natural Gas	
Composition *	95% Methane	
Fuel supply pressure	mbar	50 - 240



Container version

- Soundproofing provided by high-density volcanic rock wool
- High mechanical resistance
- Low level of noise emissions
- Door with window to visualize control panel, alarms and measurements
- Reinforced lifting points for crane hoisting and lower ones for transportation by forklift
- Residential steel silencer with -35dB attenuation and tilting cap in the exhaust
- Anti-vibration shock absorbers
- Steel chassis
- Manual oil extraction pump
- Robust construction designed for continuous or emergency applications
- Stainless steel fittings
- Emergency stops
- Easy access to the power connection
- Reinforced chassis for heavy range
- Easy access for chassis cleaning
- Silent-block with anti-corrosion protection between the genset and the chassis
- Easy access to fill radiator through the roof



Gas ramp

- Manual shut-off valve
- Gas filter
- Double solenoid valve
- High pressure regulator
- Primary pressure regulator
- Low pressure switch
- High pressure switch
- Valve (tightness) testing system
- Inlet pressure manometer
- Outlet pressure manometer
- Special Start/Stop sequence